



CUSTOM POWER DESIGN

ELECTRONICS CONSULTANTS PROVIDING CUSTOM DESIGN, DEVELOPMENT, TEST & SUPPORT



Tel: + 44 (0)118 983 1222

A DIVISION OF SMET LTD

www.custompsdesign.com

Unit 1, The Forge, Reading Road, Burghfield Common, Reading, RG7 3BL.

custom@custompsdesign.com

1500 WATT 'HANDY MAINS' INVERTERS (115V AC).

MODEL	INPUT	OUTPUT SOCKET	MODEL	INPUT	OUTPUT SOCKET
SM 4250	12V DC	DOUBLE CEE Form Outlet	SM 4255	24V DC	DOUBLE CEE Form Outlet
SM 4251	12V DC	DOUBLE IEC 'KETTLE'	SM 4256	24V DC	DOUBLE IEC 'KETTLE'
SM 4252	12V DC	DOUBLE EURO SHUKO	SM 4257	24V DC	DOUBLE EURO SHUKO
SM 4253	12V DC	UK + SHUKO	SM 4258	24V DC	UK + SHUKO

THESE UNITS ARE AVAILABLE IN OTHER INPUT VOLTAGES (UP TO 144V DC) BY SPECIAL ORDER.

ACCESSORIES: SM 2793 Heavy Duty Wiring Kit, 2 metres long, for easy battery connection.



PICTURE REPRESENTATIVE OF RANGE

- VIRTUALLY SILENT USE (FAN ONLY).
- HIGH OUTPUT POWER IN COMPACT SIZE.
- LATEST 'POWER PUSH' © SURGE HANDLING.
- VERY HIGH CONVERSION EFFICIENCY.
- REMOTE ON / OFF CONTROL FACILITY.

GENERAL DESCRIPTION. Small floor mounting converters, available with other input and output voltages, generating 115V mains level power, capable of powering most equipment from any 12 or 24 volt battery systems (model specific). Models with appropriate sockets are available to suit all needs.

Input negative is connected to case, but can be isolated by special order (contact sales). The output is isolated via a safety barrier from the input.

The output is a stepped quasi AC sine wave of nominally 115V RMS with a peak voltage appropriate to 115VAC mains. The output is suitable for almost all equipment.

The specification allows for up to 1500 watts of continuous power to be used, with up to 2 minutes at 2000 watts, accommodating disk drive run-up, motor start, etc. New 'power push' technology usually allows operation of equipment drawing a starting surge of over 9 kilowatts.

The battery input is via flat 5 mm screw terminals mounted on the rear of the unit. The unit may be turned off and on remotely, by a low current control input supplied from battery positive via a small switch.

CONNECTION: A Heavy Duty Wiring Kit, part no. SM2793, is available, consisting of 16mm² cable, 2 metres long, terminated in suitable heavy duty eyelet terminals.

BATTERY SELECTION: Only heavy-duty (high discharge rate) batteries are suitable as a power source. Fully sealed types should be used in enclosed spaces (especially inside the home). Ordinary car batteries are only suitable in well ventilated areas.

SPECIFICATION:	12V TYPES	24V TYPES
<u>INPUT</u>		
Battery:	12V nominal.	24V nominal.
Voltage Range:	11V-15V.	21.6V-30V.
Current, No Load:	0.5A	0.35A
Per 10W loading:	1 A	0.5A
Remote On/Off:	The units draw <1mA until the control input is connected to battery positive.	

<u>OUTPUT</u>		
Output Voltage:	115V ± 7V RMS. from inverter.	
Frequency:	50Hz nominal, 48Hz to 53Hz.	
Output Wave Form:	Quasi sine wave.	
Capacitive load:	6uF maximum.	
Power, Nominal:	1500W continuous (resistive).	
Power, Short term:	2000W for 2 minutes.	
'Power Push' onset:	Output current >100A minimum.	
Protection:	Current and temperature limit.	

<u>GENERAL</u>	
Size:	170mm x 155mm x 180mm.
Weight:	3.4 Kg.
Storage Temperature:	-40 to +70C.
Operating Temperature:	-20 to +35C.
Manufacturer:	Made in the United Kingdom.

CAUTION: This adaptor is supplied on the basis of the user determining the suitability for the purpose for which it is to be used. Do not use in a moving vehicle without the consent of the vehicle maker. Do not use for aviation or marine applications without written agreement. Do not use for life dependent applications. The negative input lead is connected to case and output ground making the unit suitable only for negative earth systems. We reserve the right to change the specification without notice

We manufacture a wide range of DC-DC converters, DC-AC (mains) inverters and many other power systems.

We specialise in the custom design of Hydrogen Stack converters up to 10KW.

We reserve the right to change the specification without notice

Document 4250-993